

Plug into the current future with



Unit 23, Ruimsig Boulevard Shopping Centre, Amorosa, Roodepoort, 1724, South Africa / PO Box 1449, Ruimsig 1732

Reg. No: 2012/102270/07 / VAT No: 4430267486 / T: 082 256 7430 / lizette@freedomwon.co.za

## SPECIFICATION SHEET- Freedom Lite Home and Business LiFePO4 ENERGY STORAGE

The following specifications pertain to the **Freedom Lite Home and Business** range of 52V lithium iron phosphate batteries manufactured by Freedom Won. For larger models refer to the **Freedom Lite Industrial** range.

Freedom Lite	Home 5/4	Home 10/7	Home 15/11	Home 20/14	Home 30/21	Business 40/28	Business 60/42	Business 80/56
Max Energy [kWh]	5	10	15	20	30	40	60	80
Energy, 70% DoD [kWh] (1)	3,5	7	11	14	21	28	42	56
Energy, 90% DoD [kWh]	4,5	9	13,5	18	27	36	54	72
Current Capacity [Ah]	100	200	300	400	600	800	1200	1600
Max & Cont. Charge Current [A]	100	200	300	400	600	600	800	800
Max & Cont. Charge Power [kW] (2)	5	10	15	20	30	30	40	40
Max/Cont. Discharge Current [A] (2)	300/240	300/240	480/400	480/400	750/600	750/600	1000/800	1000/800
Max/Cont. Discharge Power [kW] (2)	15/12	15/12	24/20	24/20	38/30	38/30	50/40	50/40
Max Recommended Inverter Total Rated Power (cont.) [kVA]	10	10	15	15	25	25	35	35
Nominal Voltage [V]	52V, to suit 48V Inverters, min 47V, max 56V							
Weight [kg]	60	108	158	211	310	412	613	811
Dimensions on or against wall - Height x Width x Depth [mm]	587x372x265	976x372x265	976x540x265	976x708x265	976x1046x265	1895x584x310	1895x859x310	1895x1142x310
Enclosure	Aluminium – powder coated white front rated for indoor use							
DC Connection – Fly Leads, [no. per electrode] (3)	1x 50mm <sup>2</sup>	1 x 50mm <sup>2</sup>	2 x 50mm <sup>2</sup>	2 x 50mm <sup>2</sup>	2 x 95mm <sup>2</sup>	2 x 95mm <sup>2</sup>	2 x 95mm <sup>2</sup>	2 x 95mm <sup>2</sup>
External Interfacing – (4)	<p><i>DB15 Plug</i> – 48V Relay Control and Analogue Outputs. Relay control – Separate Remote Enable for Inverter, Charger, Solar Charge Controller and a Multi-Purpose Programmable Output. Analogue Outputs – 0-5V Signals for Charge Current Limit, State of Charge.</p> <p><i>RJ45 Socket x 2</i> – CAN Bus for Interfacing with Compatible Inverters and System Controllers, connection of parallel batteries.</p>							
Protection	Shunt Trip Circuit Breaker sized to suit max current, can be tripped by BMS if critical fault, manual reset. Includes overcurrent, cell under and over voltage, temperature, weak cell detection, minimum SOC control							
Human Interface	State of Charge Display (0 to 100%), Error light, Error Reset Button, Serial RS232 Plug for Programming (note the Lite 80/56 has a CAN port for programming and not a serial port), WiFi remote monitoring (optional accessory)							

Plug into the current future with



Warranty [5]	10 years or 4 000 cycles for average 80% DoD, and max 90% DoD
Service Life [5]	>16 years (>6 000 cycles) expected life at 70% DoD (1), >20 years (>7 500 cycles) at 50% DoD
Essential Accessories	Note that for connecting the battery to a PC a special adapter is required: Lite 5/4 up to Lite 60/42 - Serial RS232 to USB adapter (must be the brand supplied by Freedom Won) Lite 80/56 - CANdapter (available from Freedom Won)

### Notes to Specification Sheet:

- 1) DoD = Depth of Discharge, recommended 70% DoD on average for extended life, 50% DoD on average for optimal life – max for normal operation 90% DoD, max for system in standby 100% DoD.
- 2) Applies to both charge and discharge. Max load duration – 5 minutes per 30 minute cycle. 2 x Max overload can be handled for 2 seconds.
- 3) Fly Leads 1,8m long, power cable Red = Positive, Black = Negative, conductors in table refer to one electrode i.e. per positive and negative connections
- 4) The hardwired control is via a DB15 plug and the CAN control is via a ethernet cable (may be non-standard pin configuration for some inverters). If Hard Wired control is required enquire about Freedom Won accessories eg control harness, contactor box, relay box.
- 5) End of Life (EoL) defined as cell dropping to 60% of Beginning of Life (BoL) capacity for expected life and 70% of BoL capacity for warranty. This warranty applies to Lites sold after 1 September 2019. For Lites sold prior please contact Freedom Won for warranty information.

Date Issued – 9 September 2019